

DataFire SYNC 2000 Cables

DataFire SYNC 2000 SCSI Connector Pinout

| SIGNAL | SCSI J1 | SCSI J2 | NOTES |
|---------------|----------------|----------------|-----------------------------|
| ID0 | 1 | -- | OPEN |
| ID1 | 35 | -- | OPEN |
| ID2 | 2 | -- | OPEN |
| ID3 | 36 | -- | TIED TO SHELL ON 68 PIN END |
| GND | SHELL | SHELL,A,B | USE BRAID TO CONNECT SHELLS |
| 103B TxD+ | 4 | S | TWISTED PAIR |
| 103A TxD- | 38 | P | |
| 113B TxCLKo+ | 5 | W | TWISTED PAIR |
| 113A TxCLKo- | 39 | U | |
| 105B RTS+ | 6 | | |
| 105A RTS- | 40 | | |
| 108B DTR+ | 7 | | |
| 108A DTR - | 41 | | |
| 104B RxD+ | 8 | T | TWISTED PAIR |
| 104A TxD- | 42 | R | |
| 115B RxCLKi+ | 43 | X | TWISTED PAIR |
| 115A RxCLKi- | 9 | V | |
| 114B TxCLKi+ | 10 | AA | TWISTED PAIR |
| 114A TxCLKi- | 44 | Y | |
| 106B CTS+ | 11 | | |
| 106A CTS- | 45 | | |
| 107B DSR+ | 12 | | |
| 107A DSR- | 46 | | |
| 109B DCD+ | 13 | | |
| 109A DCD- | 47 | | |
| 107 DSR | 14 | E | TWISTED PAIR |
| 109 DCD | 48 | F | |
| 105 RTS | 16 | C | TWISTED PAIR |
| 108 DTR | 50 | H | |
| 106 CTS | 52 | D | TWISTED PAIR |
| GND | SHELL | SHELL | |